



Features

- IGBT Based Rectifier
- True Online Double Conversion with DSP Control Technology for High Performance and Reliability.
- New Graphical LCD Display Provides UPS Data, Alarms and Helps in faults diagnostics and trouble shooting.
- Double Conversion Efficiency upto 90%.
- Active Input Power Factor Correction 0.99.
- 0.9 Output Power Factor.
- Wide Input Voltage window (110 - 280 Vac) for Indian
- Environmental Condition and for Optimized Battery Performance.
- Configurable Output Voltage (200/208/220/230/240 Vac.)
- Generator Compatible with Wide Input Frequency Range (40 Hz-70 Hz).
- 4 Stage Extendable Charging Design for optimized Battery Performance.
- Adjustable Battery Charging Current up to 12A according to Battery Capacity and Rating.
- 50/60 Hz Automatic Frequency Converter Mode.
- Intelligent Monitoring with Standard RS232/USB Port Plus Slot Available for RS485/Dry Contact/SNMP Card.
- Inbuilt OVCD.

True Online Double Conversion UPS with extended runtime capabilities

Liebert® GXT MT+ Series systems is true double conversion online UPS systems designed to provide with a capacity of 10-20kVA. Liebert® GXT MT+ units feature total isolation of the load from the mains - isolating input and output sections, and making the systems ideal for Data Networks / Small Data Centers/VOIP application. The units support hot standby configuration, making them suited for critical applications like banks.



Liebert® GXT-MT+ 10-20 kVA (3X1)

Technical Specifications

Model	GXT MT+ 10KVA (3X1)	GXT MT+ 20KVA (3X1)
Phase	3 phase in / 1 phase out	
Capacity	10000 VA / 9000 W	20000 VA / 18000 W
Input Characteristics		
Nominal Voltage	3 x 400 VAC (3Ph+N)	
Voltage Range	305-478 VAC (3-phase) @ 100% load	
Frequency Range	46-54 Hz or 56-64Hz	
Power Factor	≥ 0.99 @ 100% load	
Thdi	< 6% @ 100% load	
Output Characteristics		
Output Voltage	208**/220/230/240VAC	
Voltage Regulation	± 1%	
Frequency Range (Synchronized Range)	46-54Hz or 56-64Hz	
Frequency Range (Batt. Mode)	50 Hz ± 0.1 Hz or 60 Hz ± 0.1 Hz	
Current Crest Ratio	3:1 (max.)	
Harmonic Distortion	≤ 2 % THD (Linear Load) ; ≤ 5 % THD (Non-linear Load)	
Transfer Time	zero	
Waveform	Pure Sinewave	
Ac Mode Efficiency	>92%	
Eco Mode Efficiency	97%	
Battery Characteristics		
Battery Type	Lead acid/Tubular/Li-ion	
Numbers	18-20***(adjustable)	
Charging Current (Max.)	12A settable to 2/4/6/8/10/12 Amps	
Charging Voltage	273 VDC ± 1% (Based on 20pcs batteries)	
Indicators		
Lcd Panel	UPS status, Load level, Battery level, Input/Output voltage, Discharge timer, and Fault conditions	
Alarm		
Battery Mode	Sounding every 4 seconds	
Low Battery	Sounding every second	
Overload	Sounding twice every second	
Fault	Countinuously sounding	
Physical		
Dimension, D X W X H (mm)	592 X 250 X 576	592 x 250 x 826
Net Weight (Kgs)	28	45
Environment		
Operation Humidity & temperature	0-95 % RH @ 0- 50°C**** (non-condensing)	
Noise Level	< 58dB @ 1 Meter	< 60dB @ 1 Meter
Management		
Smart Rs-232/Usb	Supports Windows® 2000/2003/XP/Vista/2008, Windows® 7/8, Linux, Unix, and MAC	
Optional SNMP	Power management from SNMP manager and web browser	

* Product specifications are subject to change without further notice

**Derate capacity to 90% of capacity when the output voltage is adjusted to 208VAC

***When using batteries from 18-19, the unit will be de-rate according to formula ; P= Prating X N/20

**** Derate to 80% capacity when ambient temperature is 45°-50°



Vertiv.com/en-in | E-mail : marketing.india@vertiv.com | Toll free : 1-800-2096070

Vertiv Energy Private Limited | Plot C-20, Rd No.19, Wagle Ind Estate, Thane (W), 400604. India

© 2019 Vertiv Co. All rights reserved. Vertiv, and the Vertiv logo trademarks or registered trademarks of Vertiv Co. All other names and logos referred to are trade names, trademarks or registered trademarks of their respective owners. While every precaution has been taken to ensure accuracy and completeness herein, Vertiv Co. assumes no responsibility, and disclaims all liability, for damages resulting from use of this information or for any errors or omissions. Specifications are subject to change without notice.